

True circular polarization

Handles up to 25 kW per bay

Multiplexes over 6 MHz bandwidth

using coax broadbanding technology

Shively standard Features:

- Consistently predictable patterns
- Digital-ready
- Pattern studies available
- No factory personnel needed to install
- Adjustable fine-matching transformer
- Radomes and deicers available
- Rugged stainless steel corrosion-resistant mounts
- Works with regular towers; no need for special frequency-sensitive tower sections
- Pressure relief valve for easy purging of the system
- Special spacing, H/V ratios, null fill and beam tilt available



Performance specifications:

Polarization: Right circular.

VSWR: 1.05 : 1 ± 200 kHz for a single-frequency antenna
1.1 : 1 over ± 200 kHz for a dual frequency antenna with up to 6 MHz frequency separation.

Azimuth pattern circularity: Horizontal component ± 1.5 dB on pole.

Input connection: Standard up to 40 kW; 3-1/8" female flange; end-fed 2 - 7 bays; center-fed over 7 bays
Special on request: up to 80 kW input; 4-1/16" male or 6-1/8" male flange.

Electrical specifications:

| No. of Bays | Gain | | Input Power Rating, kW | | No. of Bays | Gain | | Input Power Rating, kW | |
|-------------|-------|-------|------------------------|------------|-------------|-------|------|------------------------|------------|
| | Power | dB | End-fed | Center-fed | | Power | dB | End-fed | Center-fed |
| 2 | 0.71 | -1.51 | 25 | 50 | 7 | 2.23 | 3.48 | 40 | n/a |
| 3 | 1.02 | 0.08 | 40 | n/a | 8 | 2.54 | 4.04 | 40 | 80 |
| 4 | 1.32 | 1.19 | 40 | 80 | 10 | 3.14 | 4.97 | 40 | 80 |
| 5 | 1.62 | 2.10 | 40 | n/a | 12 | 3.75 | 5.74 | 40 | 80 |
| 6 | 1.92 | 2.84 | 40 | 80 | | | | | |

Notes:

1. End-fed arrays include 3-1/8" EIA input. Center-fed arrays include 3-1/8" EIA input (6-1/8" EIA and 4-1/16" optional).
2. Our gain figures are derived from the computed directivity and include the losses in the antenna feed system.
Gain is provided for one polarization and is equal in circularly polarized antennas for both horizontal and vertical components. Gain will be reduced if null fill, beam tilt, special H/V ratio, or special wavelength spacing is provided. Gain will increase in a directional array by the directivity of the azimuth pattern.

Document No. ds-6814-hw (170322)

A Division of Howell Laboratories, Inc., P. O. Box 389, Bridgton, Maine 04009 USA
(207) 647-3327 1-888-SHIVELY Fax: (207)647-8273
An Employee-Owned Company

www.shively.com
sales@shively.com
Certified to ISO-9001

Model 6814 size and weight (half-wave-spaced):

| No. of Bays | Vertical Tower Space | | | | | | Weight | | | | | |
|-------------|----------------------------|------|---------------------|------|-------------------------------|------|-----------------|------|--------------|-------|---|-------|
| | Antenna Radiation Aperture | | Physical Space Used | | Total Tower Space Recommended | | Without radomes | | With radomes | | With radomes & 1/2" (1.2 cm) radial ice | |
| | ft | m | ft | m | ft | m | lb | N | lb | N | lb | N |
| 2 | 5 | 1.6 | 14 | 4.6 | 25 | 8.2 | 190 | 845 | 430 | 1912 | 663 | 2948 |
| 3 | 10 | 3.3 | 19 | 6.2 | 30 | 9.8 | 255 | 1134 | 615 | 2734 | 954 | 4241 |
| 4 | 15 | 4.9 | 24 | 7.9 | 35 | 11.5 | 320 | 1423 | 800 | 3557 | 1245 | 5535 |
| 5 | 20 | 6.6 | 29 | 9.5 | 40 | 13.1 | 385 | 1712 | 985 | 4379 | 1536 | 6829 |
| 6 | 25 | 8.2 | 34 | 11.2 | 45 | 14.8 | 450 | 2001 | 1170 | 5202 | 1828 | 8127 |
| 7 | 30 | 9.8 | 39 | 12.8 | 50 | 16.4 | 515 | 2290 | 1355 | 6024 | 2119 | 9421 |
| 8 | 35 | 11.5 | 38 | 12.5 | 55 | 18.0 | 620 | 2756 | 1580 | 7025 | 2457 | 10924 |
| 10 | 45 | 14.8 | 48 | 15.7 | 65 | 21.3 | 750 | 3334 | 1950 | 8670 | 3040 | 13516 |
| 12 | 55 | 18.0 | 58 | 19.0 | 75 | 24.6 | 880 | 3912 | 2320 | 10314 | 3622 | 16103 |
| 14 | 65 | 21.2 | 68 | 22.2 | 85 | 27.8 | 1010 | 4490 | 2690 | 11959 | 4205 | 18695 |
| 16 | 75 | 24.4 | 78 | 25.4 | 95 | 30.6 | 1140 | 5068 | 3060 | 13604 | 4787 | 21283 |

Windload (half-wave-spaced):

| No. of Bays | Without radomes | | | | With radomes | | | | With radomes & 1/2" (1.2 cm) radial ice | | | |
|-------------|------------------|----------------|------------------|----------------|------------------|----------------|------------------|----------------|---|----------------|------------------|----------------|
| | EPA _N | | EPA _T | | EPA _N | | EPA _T | | EPA _N | | EPA _T | |
| | ft ² | m ² | ft ² | m ² | ft ² | m ² | ft ² | m ² | ft ² | m ² | ft ² | m ² |
| 2 | 9.4 | 0.9 | 8.8 | 0.8 | 17 | 1.6 | 14.1 | 1.3 | 23.4 | 2.2 | 19.8 | 1.8 |
| 3 | 13.2 | 1.2 | 12.7 | 1.2 | 24.3 | 2.3 | 20.3 | 1.9 | 33.8 | 3.1 | 28.8 | 2.7 |
| 4 | 17.1 | 1.6 | 16.5 | 1.5 | 31.5 | 2.9 | 26.4 | 2.5 | 44.2 | 4.1 | 37.8 | 3.5 |
| 5 | 20.9 | 1.9 | 20.4 | 1.9 | 38.8 | 3.6 | 32.5 | 3.0 | 54.6 | 5.1 | 46.8 | 4.3 |
| 6 | 24.8 | 2.3 | 24.3 | 2.3 | 46.1 | 4.3 | 38.7 | 3.6 | 65 | 6.0 | 55.7 | 5.2 |
| 7 | 28.6 | 2.7 | 28.1 | 2.6 | 53.3 | 5.0 | 44.8 | 4.2 | 75.4 | 7.0 | 64.7 | 6.0 |
| 8 | 33.6 | 3.1 | 32.5 | 3.0 | 61.6 | 5.7 | 51.3 | 4.8 | 86.6 | 8.0 | 74 | 6.9 |
| 10 | 41.3 | 3.8 | 40.2 | 3.7 | 76.2 | 7.1 | 63.6 | 5.9 | 107.4 | 10.0 | 92 | 8.5 |
| 12 | 49 | 4.6 | 48 | 4.5 | 90.7 | 8.4 | 75.8 | 7.0 | 128.2 | 11.9 | 109.9 | 10.2 |
| 14 | 56.7 | 5.3 | 55.7 | 5.2 | 105.2 | 9.8 | 88.1 | 8.2 | 149 | 13.8 | 127.9 | 11.9 |
| 16 | 64.4 | 6.0 | 63.4 | 5.9 | 119.8 | 11.1 | 100.4 | 9.3 | 169.8 | 15.8 | 145.8 | 13.5 |

Notes:

1. Ask for technical assistance at Shively for weight and windload information on ice thicker than 1/2 in.
2. The mounting structure must not flex more than $\pm 3/4$ in (± 1.8 cm) in any 10-ft (3-meter) section. 5 feet (1.5 m) of mounting structure is required above and below the antenna bays for proper pattern formation.
3. Antenna radiation aperture is the distance from the center of the top bay to the center of the bottom bay. Physical space used is from the top of the top bay to the input flange at the bottom of the array, or the bottom of the bottom bay in a center-fed array. Total tower space recommended allows ten feet (3 m) of clear tower space above and below the antenna to protect from pattern interference by other antennas. At frequencies lower than 98 MHz, each of these dimensions will increase by up to 1 ft (0.3 m) per bay.
4. Seven bays or less are normally end-fed. All antennas supplied with beam tilt will be center-fed. Antennas with an odd number of bays are normally not available with center feed.
5. 1/2" radial ice is at 200 ft above ground with a design ice thickness of 0.21".
6. Windload and weight tabulations are estimates and assume 98 MHz. They include the bay, interbay feedline, input connection, and a fine-matching transformer. No values have been included in these tabulations for mounts. Actual values vary with the specific installation. Contact us with details of your installation if more precise values are needed.
7. Antenna areas and weights calculated using TIA-222-G.
8. Deicers add approximately 1 lb (4.4 N) per bay in weight and 2 lb (8.9 N) or 0.05 ft² (0.005 m²) per bay in windload.
9. Ask for technical assistance at Shively if you are planning to mount antennas on AM towers or install them at altitudes over 3,000 ft (915 m) above mean sea level.